

## **DESN2000 (Computer Engineering) 2024 T2**

### **Lab sheet 1 (weeks 1 and 2)**

Last edited: 27/05/2024

See the “Assessment Guide for Laboratory Exercises” document on the course page for details on marking. You should use the provided UNSW coaST board for these exercises. Make reasonable assumptions if not explicitly stated and state such assumptions to your demonstrator when getting marked.

#### **Task 1 (20%)**

Write a programme that turns on the corresponding direct LED on the development board as long as the corresponding direct button is pressed. For example, when SW1 is pressed, D1 should light up. When multiple buttons are pressed, all the corresponding LEDs should light up.

#### **Task 2 (20%)**

Write a programme that shows the lower nibble (the four lower significant bits) of a 16-bit number on the LEDs D4-D1. D4 should have the most significant bit of the nibble. The 16-bit number can be hardcoded in your programme as an uint16\_t integer variable.

#### **Task 3 (30%)**

Write a programme that moves a 16-bit pattern on the LED bar. The pattern can be a hardcoded uint16\_t integer variable which you can define as for example “uint16\_t pattern = 0b0000111100001100”. By default the pattern should move to the right and the right corner should wrap to the left corner. Pressing the SW1 button should change the direction of the pattern movement. Make sure your buttons are appropriately debounced in the software.

#### **Task 4 (30%)**

Write a programme that increments a binary counter on the LED bar when SW1 is pressed. Initially, the counter starts with 0. When SW2 is pressed, the counter should decrement. You should make sure the counter does not overflow or underflow. Pressing SW3 should reset the counter to 0. Pressing SW4 should set the counter to the maximum possible count. You must make sure the buttons are debounced in the software so that one press only leads to one increment/decrement.